

XPH Series

175–420 W

Compact High Power Bench DC Power Supplies

18–75 V

- Low noise
- Excellent line/load regulation
- Coarse and fine voltage controls
- Constant voltage or constant current operation with automatic crossover and mode indication
- Individual On/Off switch per output (not including fixed output)
- Switchable 3.3 V/5 V output on triple output model
- Switchable remote sense



2–20 A

~

115

230

The Xantrex XPH Series provides 175 to 420 watts of programmable DC power. The XPL is a compact, high performance, low cost power supply suited for benchtop applications.

The XPH Series uses combined switchmode pre-regulation with linear post-regulation to provide performance comparable with an all-linear design. The XPH features excellent line and load regulation with low noise and good transient response. The XPH Series is available in a single, dual and triple output for benchtop use.

The XPH dual output models have two independent and isolated outputs with its own On/Off switch. The outputs can be wired in either series or parallel to provide higher voltage or higher current output. All outputs are intrinsically short circuit proof, and are protected against external voltages and reverse currents. The XPH triple-output model has the same features as the dual-output model with an additional switchable fixed output of 3.3 volts and 5 volts.

Output voltages up to 150 volts

The XPH-M Series is a dual-output 300-watt power supply with multi-mode capability. This enables it to operate as a dual power supply with two independent and isolated outputs, or as a single power supply of double the power. As a dual, each output provides 0 to 75 volts at 0 to 2 amps (mode A). As a single the output can be selected as either 0 to 75 volts at 0 to 4 amps (mode B) or 0 to 150 volts at 0 to 2 amps (mode C). In single modes, the unused half of the unit becomes completely inoperative and its displays are blanked.

Higher currents and remote sense

The XPH-R series are single-output power supplies similar in size and weight to the standard XPH series but offering higher output currents. To match their higher current capability, XPH-R models include switchable remote sensing and XPH extended voltmeter resolution.

Suitable for 42-volt automotive

The XPH 42-20 provides 420 watts of power within a highly compact and lightweight unit. It can provide current of up to 10 amps at voltages up to 42 volts in both constant voltage and constant current modes. The choice of 42 volts enables it to be used as a test source for the new generation of automotive electrical parts which will use 42 volts (18-cell batteries) instead of 14 volts (six-cell batteries), thus reducing currents and hence wiring losses. Switchable remote sense is provided to remove the effects of connection lead resistance at high current.

**Programmable Division
Xantrex Technology Inc.**
9250 Brown Deer Road
San Diego, CA 92121-2267
USA

xantrex

XPH Series : Product Specifications

Output : Voltage and Current				
Models	Output Voltage	Output Current	Output Power	Outputs
XPH 18-10	0-18 V	0-10 A	180 W	1
XPH 20-20	0-20 V	0-20 A	400 W	1
XPH 35-5	0-35 V	0-5 A	175 W	1
XPH 35-4D	0-35 V	0-4 A	280 W	2
XPH 35-4T	0-35 V	0-4 A	305 W	3
XPH 42-10	0-42 V	0-10 A	420 W	1
XPH 75-2D	0-75 V	0-2 A	300 W	2
Output Terminals				
Standard	Type 4 mm "binding post" terminals suitable for plugs or wires			
XPH 75-2D only	As above but with fully "touch proof" construction			
Optional (all models)	4 mm safety sockets, suitable for shrouded plugs			
Input				
AC Input	110-240 V \pm 10%, 50/60 Hz (XPH 35-5, XPH 35-4D, XPH 35-4T, XPH 75-2D) Factory set: 110-120 Vac \pm 10% or 220-240 Vac \pm 10%, 50/60 Hz Installation Category II (XPH 18-10, XPH 42-10)			
Consumption	400 VA (XPH 35-5, XPH 18-10) 500 VA (XPH 35-4D, XPH 35-4T, XPH 75-2D) 800 VA (XPH 20-20), (XPH 42-10)			
General Specifications				
Operating Mode	Constant voltage or constant current with automatic cross-over and indication			
Voltage Setting	By coarse and fine controls			
Current Setting	By single logarithmic control			
Output Impedance	Typically < 5 m Ω in constant voltage mode. Typically > 50 k Ω (XPH35-4, XPH75-2D), > 20 k Ω (XPH35-5, XPH42-10), > 10 k Ω (XPH18-10)			
Line regulation	< 0.01% of max. output for a 10% line voltage change			
Load regulation	< 0.01% of max. output for a 90% load change, < 0.1% (XPH75-2D in Mode C)			
Ripple & Noise Typically	< 2 mVrms, < 10 mVpk-pk, < 15 mV (XPH75- 2D), CV mode (20 MHz bandwidth)			
Transient Response	< 200 μ s to within 50 mV of set level for 90% load change (mode A only XPH75-2D)			
Temperature Coefficient	Typically < 100 ppm / $^{\circ}$ C			
Output Protection	Outputs will withstand forward voltages up to 40 V (XPH 35-5, XPH 35-4D, XPH 35-4T) or 85V/170V (XPH 75-2D)			
Status Indication	Output ON lamps. Constant current mode lamps			
Output Switch	Electronic. Preset voltage/current displayed with output off.			
Output Terminals	4 mm terminals on 19 mm (0.75") pitch. Special safety terminals on XPH 75-2D			
Remote Selection	Switch selectable as Local or Remote			
Connection	Remote sense connections via spring-loaded connectors			
Regulatory	CE-marked units meet: EN61010-1 and EN61326			
Meters (main outputs)				
Meter Types	Separate four-digit meters for voltage and three-digit meter current with 14 mm (0.56") LED displays. Reading rate 4/sec			
Meter Resolutions	100 mV, 10 mA			
Meter Accuracy				
Voltage	0.3% \pm 1 digit			
Current	0.6% \pm 1 digit			

